

VISTA-10P CONTROL PANEL



Honeywell's feature-rich VISTA-10P is the industry's most economical and versatile control panel. It's ideally suited for a wide range of applications. The six-zone panel significantly reduces dealer training and service call costs thanks to user-friendly features that make operation easier than ever. In addition, it increases upsell opportunities through its expansion capabilities and flexibility.

FEATURES

- Six hardwired zones on board
 - 16 wireless expansion zones totaling 22 protection zones
 - Eight independent keyfob zones allow two wireless keys to be programmed without using any of the 22 zones
 - 32 Event log
 - 16 user codes
 - One configurable zone type allows installers to create their own custom zone type
 - Two on-board triggers
 - Four output devices using a 4204 relay module
- Valuable End-User Features**
- Flexible function keys allow single button arming
 - One programmable macro key
 - Viewable on system keypad display
 - Exit countdown
 - Time and date*
 - Event log*
 - Two schedules
 - Can activate relays on programmed times or on events
 - Latchkey reports to a pager
 - “User Access” time windows
 - Chime by zone
- 4286 Phone Module allows system control from any touchtone phone
 - Four output devices with multiple actions per device
 - Turn lights on when system disarms with a 4204 Relay
 - Flash same lights when system is in alarm using a 4204 Relay
- * with Alpha Keypad

VISTA-10P

CONTROL PANEL

SPECIFICATIONS

Electrical

- Aux power 12VDC, 600mA max
- Seven hour standby at 400 mA aux load with four amp hour battery
- 16.5VAC/25VA transformer
- Alarm output 12VDC, 2.0 amps max
- For UL installations, combined aux and alarm output cannot exceed 700mA

Output Control

- Supports multiple output devices, one 4204 and two triggers

Zones

- Six hardwired zones
- Selectable response: 10msec, 350msec, 750msec
- 16 selectable zone types plus one configurable zone type
- Programmable swinger suppression

Expansion Devices

- 4204 – Up to four relays – 15mA standby (each active relay draws an additional 40mA)

Accessories

- 4286 VIP Voice Module – 220mA
- 5881ENL supports up to eight zones – 60mA, 5881ENM supports up to 16 zones – 50mA, 5883 Transceiver supports up to 16 zones – 80mA
- Supports Eagle 1225 and 1221 boards

Keypads

- 6160 Custom Alpha (required for programming) – 100mA
- 6160V Custom Alpha Voice – 100mA
- 6150 Fixed English LCD – 85mA/40mA
- 6150V Fixed English Voice LCD – 85mA/40mA
- 6150RF Fixed English RF LCD – 85mA/40mA
- 6148 Fixed English LCD – 70mA/30mA

Agency Listings

- UL Residential Fire, Burglary and CSFM

Smoke Detectors

- Supports four-wire smoke detectors

Communications

- Touchtone or pulse
- Formats supported
 - ADEMCO Contact ID
 - ADEMCO 4 + 2 Express
 - ADEMCO low speed
 - SESCOA/RADIONICS
- 3 + 1, 4 + 1 and 4 + 2 reporting
- Reporting capabilities
 - Split
 - Dual
 - Split/Dual - True dial tone detection
- Low battery reports 11.2 – 11.6VDC
- AC loss and restoral reporting supported

ORDERING

VISTA-10P

VISTA10P Control Panel

Honeywell Security & Custom Electronics

Honeywell International Inc.
PO Box 9035
Syosset, NY 11791
www.honeywell.com

RE06040
L/VISTA10P/D
August 2006
© 2006 Honeywell International Inc.

Honeywell