

6160CR

COMMERCIAL FIRE ALPHA KEYPAD



The 6160CR is an addressable remote keypad intended for use in commercial fire applications with Honeywell's control platforms. The keys are continuously backlit for convenience and easy visibility. The LCD display is backlit

only when a key is depressed*, or when the system is in alarm or trouble condition.

* Note: On some platforms, the LCD may be programmed to remain on at all times (see panel instructions for details).

FEATURES

- Four programmable function keys
- Built-in sounder
- Four LEDs
 - Armed
 - Ready
 - Trouble
 - Supervisory
- Large easy-to-read display
- Red removable door
- Physical
 - 5.250" W x 7.437" H x 1.312" D

SPECIFICATIONS

Display

- Alphanumeric, 32-character (2 lines x 16 characters)
LCD back light LEDs:
Armed (red)
Ready (green)
*Trouble (yellow)
*Supervisory (yellow)
- See control panel's instructions for specific applications regarding Trouble and Supervisory LEDs.

Sounder

- High-quality speaker

Electrical

- 45mA standby 150mA in alarm (sounder, back light and LED on)

Wiring Table (All keypads)

DI	"Data IN" to control panel from keypad
-	Ground (-aux. Power)
+	+12VDC (+aux. Power)
DO	"Data OUT" from control panel to keypad

Compatibility

- Supports Control Platforms
 - VISTA-32FB Rev. 3 and higher
 - VISTA-128FB Rev. 4 and higher
 - VISTA-128FBP
 - VISTA-250FBP
 - V128FBP-24
 - V250FBP-24

UL/CUL Listed for Residential and Commercial Fire and Burg installations. To be employed with manufacturer's listed control units as indicated in the installation instructions.

ORDERING

6160CR

Commercial Fire Alpha Keypad

Honeywell Security & Custom Electronics

Honeywell International Inc.
PO Box 9035
Syosset, NY 11791
www.honeywell.com

Honeywell